



Frequency coverage in band switch with frequency multiplier & fine controls

The Digital Function Generator is a useful test instrument capable of generating multiple waveforms like sine, square and triangle at any required frequency, in switched decade sub-ranges. The generator has output banana sockets; and a maximum wave output of 100mV to 20 volts peak to peak, which may be adjusted by a variable potentiometer control. The Function Generator has a selection to switch from sine, square and triangle waveform. The frequency of the signal is set on a dial, along with a multiplier range switch.

Specification:-

- Frequency range : 0.1Hz to 1MHz in Six ranges
- Wave forms : Sine, Square and Triangle and TTL output
- Output amplitude : 0-20V peak to peak for Sine, Triangle 0-15V peak to peak for Square
- DC Offset : $\pm 10V$ with adjustable to 0V
- Power Supply : 220volts /50Hz, +-10%
- Accessory : Connecting lead with banana plug and crocodile

Note: Specifications are subject to change, Photos shown above are Indicative, Actual Product can Vary.



Export Sales: +91-9829132777
India Sales: +91-9588842361



IT-2013, Ramchandrapura Industrial Area,
Sitapura Extension, Jaipur-302022, India.



info@tesca.in
www.tescaglobal.com