



46613 is a high accuracy 3-phase electrical energy measurement device. It is designed to measure any 3-phase electrical system simultaneously without using individual meters. It is a compact table top unit which includes signal processing required to perform Voltage, Current, Frequency, Active Power, Reactive Power, Apparent Power and Power Factor Measurements. This product is suitable to measure active, reactive, and apparent energy in various 3-phase configurations such as WYE or DELTA services. It is Compatible with both 3-phase/3-wire and 3-phase/4-wire systems. All the parameters measured are displayed simultaneously on a single display unit.

Features

- Microcontroller based design for accurate measurement
- 240 x 128 Graphical LCD Display to view all the parameters
- Simultaneous display of Three Phase electrical parameters
- Used with Single Phase / Three Phase supply
- 2 Year Warranty

Technical Specifications

Measurement	
Connection Type	: Input and Output
Input Voltage Range (Vr, Vy, Vb)	: 30 – 230 V r m s A C , Accuracy ±1%
Input Voltage Range (Vry, Vy b, Vbr)	: 50 – 450Vrms AC, Accuracy ±1%
Input Current Range (Ir, Iy, Ib)	: 0.20–10Amp, Accuracy ±1%
Frequency	: 45 – 55Hz, Accuracy ±0.5Hz
Active power	: 50 – 5000Watts, Accuracy ±2%
Reactive power	: 50 – 5000Watts, Accuracy ±2%
Apparent power	: 50 – 5000Watts, Accuracy ±2%
Auxiliary Supply	: 230V ±10%, 50Hz
Power Factor	: 0.30 to 0.99 both Lead and Lag, Accuracy ±2° Electrical

Note: Specifications are subject to change.

Tesca Technologies Pvt. Ltd.

IT-2013, Ramchandrapura Industrial Area, Sitapura Extension,
Near Bombay Hospital, Vidhani Circle, Jaipur-302022, Rajasthan, India,
Tel: +91-141-2771791 / 2771792; Email: info@tesca.in, tesca.technologies@gmail.com
Website: www.tesca.in