

Features:

- Analog Multimeter with Mirror Scale
- Inbuilt Buzzer and LED
- 0W Adjustment with x100 Range
- Transistor Test, hFE with Diode



Technical Data:-	
AC Voltage (Volts)	10-1000 V
AC Voltage Accuracy	<4% of full scale
DC Voltage Accuracy	<3% of full scale
DC Current (Amp)	0.01-10A
DC Voltage	0.1-1000 V
DC Current Accuracy	<3% of full scale
Resistance (ohm)	0-20 M Ohm
Resistance Accuracy	<3% of Arc.
Capacitance Range (F)	0.0025-25 uF
Capacitance Accuracy	<3% of full scale
Resistance Test Range	X1 , X10 , X100 , X1K (20 M Ohm max.)
Applications :	Widely used for measuring voltage, current and electrical resistance. Analog, Rotary, AC / DC V. , Resistance , DC Amp. , I/P Imp.
Heavy ABS Housing plus compact protective holster alongside.	
High input impedance 20 Kohm/DCV, 9 Kohm/ACV.	
Dry Battery Test	
Continuity Buzzer Test	
Decibel	
Diode Test	
Transistor hFE Test	
20KOhm / V	
Dimension	160 x 105 x 40 mm
Weight	380g KG

Note: Specifications are subject to change.

Tesca Technologies Pvt. Ltd.

IT-2013, Ramchandrapura Industrial Area, Sitapura Extension,
Near Bombay Hospital, Vidhani Circle, Jaipur-302022, Rajasthan, India,
Tel: +91-141-2771791 / 2771792; Email: info@tesca.in, tesca.technologies@gmail.com
Website: www.tescaglobal.com