



Technical Specifications

Digital Inputs and Outputs

- **16 Digital Inputs**
 - Voltage: DC 24 V
 - Access via 4 mm safety sockets
- **16 Digital Outputs**
 - Voltage: DC 24 V
 - Access via 4 mm safety sockets
- **Additional Digital I/O**
 - 16 Inputs and 16 Outputs available through:
 - 9-pin connector
 - 25-pin connector
 - 37-pin connector plug/socket

Input Simulation Controls

- **Pushbutton / Latching Switches**
 - 16 integrated switches for simulating digital inputs
 - Allows hands-on practice with input processing

Note: Specifications are subject to change, Photos shown above are Indicative, Actual Product can Vary.



Export Sales: +91-9829132777
India Sales: +91-9588842361



IT-2013, Ramchandrapura Industrial Area,
Sitapura Extension, Jaipur-302022, India.



info@tesca.in
www.tescaglobal.com

Analog Inputs and Outputs

- **8 Analog Inputs**
 - Voltage Range: -10 V to +10 V
 - Current Range: 0 to 20 mA
- **4 Analog Outputs**
 - Selectable between:
 - Voltage: -10 V to +10 V
 - Current: 0 to 20 mA
- **Potentiometer-Controlled Output**
 - One analog output adjustable via potentiometer
 - Supports both voltage and current ranges:
 - Voltage: -10 V to +10 V
 - Current: 0 to 20 mA

Connectors

- 9-pin and 25-pin sockets for direct mechatronic control
- 37-pin plug and socket for extended connectivity

Note: Specifications are subject to change, Photos shown above are Indicative, Actual Product can Vary.



Export Sales: +91-9829132777
India Sales: +91-9588842361



IT-2013, Ramchandrapura Industrial Area,
Sitapura Extension, Jaipur-302022, India.



info@tesca.in
www.tescaglobal.com