

Features:

- Analog Multimeter with Mirror Scale
- Inbuilt Buzzer and LED
- 0W Adjustment with x100 Range
- Transistor Test, hFE with Diode



Technical Data:-

Basic Functions	Range	Basic Accuracy of FSD	Sensitivity
DC Voltage	0.1mV ~ 1000V	3; for 1000V : 5	20KW/V
AC Voltage	10V ~ 1000V	4; for 1000V : 5	9KW/V
DC Current	50μA ~ 10A	3; for 10A : 5	
Resistance x 1	0.2.W~ 2KW	3	
x 10	2.W~ 20KW		
x 100	20W~ 200KW		
x k	200W~ 2MW		
x 10k	2KW~ 20MHz		
I _{ceo}	150mA - 15mA - 150mA		
hFE	0 ~ 1000with connector		

Special Function:

Diode test	✓
Function Protection	✓
Transistor testing	✓
Continuity Buzzer	About 100W

Standard Accessories

Test Leads, Holster, Manual

Dimension: 148(H) x 100(W) x 35(D)mm

Note: Specifications are subject to change.

Tesca Technologies Pvt. Ltd.

IT-2013, Ramchandrapura Industrial Area, Sitapura Extension,
Near Bombay Hospital, Vidhani Circle, Jaipur-302022, Rajasthan, India,
Tel: +91-141-2771791 / 2771792; Email: info@tesca.in, tesca.technologies@gmail.com
Website: www.tescaglobal.com