



Advanced Microwave Integrated Circuit Lab includes instruments and accessories for studying the characteristics of any MIC (Microwave Integrated Circuits) component over the Frequency Range 2.2 to 3GHz. Characteristics and measurements like Transmission Loss and Reflection Loss of different MIC components can be studied with the help of instruments provided with Order Code- 10411 / 10411A. Directivity and Gain of Antennas can also be measured with the setup provided. The theoretical background on these components and experimental details are provided in the learning material.

Features

- Complete setup with Generator, MIC Components and Meter.
- Gold Plated Components and Connectors.
- Microwave Generator with internal AM and FM.
- PC to PC Data Communication.
- Antenna Radiation Pattern measurement.
- Directivity and Gain measurement.
- 2 Year Warranty

This Training System Includes:

- Microwave Generator (2.2 3GHz)
- VSWR Meter
- MIC Components
- Learning Material
- Transmitting and Receiving mast

MIC Components

MIC Components	10411	10411A
50 Microstrip Line	\checkmark	\checkmark
Band Stop Filter	\checkmark	\checkmark
Parallel line Directional Coupler (15 dB)	\checkmark	\checkmark
Wilkinson Power Divider (3 dB)	\checkmark	\checkmark
Branchline Directional Coupler (3 dB)	\checkmark	\checkmark
Low Pass Filter	\checkmark	\checkmark
Band Pass Filter	\checkmark	\checkmark
Ring Resonator	\checkmark	\checkmark
Rat-Race Hybrid Ring Coupler (3 dB)	\checkmark	\checkmark
MIC Patch Antennas (2 Nos.)	\checkmark	\checkmark
Yagi antenna	\checkmark	\checkmark
Dipole Antenna	\checkmark	\checkmark
MIC Amplifier	\checkmark	\checkmark
RF Switch Optional	\checkmark	\checkmark
RF Mixer	Optional	\checkmark
Local Oscillator	Optional	\checkmark
Measuring Line	Optional	\checkmark
Isolator	Optional	\checkmark
Circulator	Optional	\checkmark
Vector Network Analyser (3MHz-3GHz)	Optional	Optional

Note: Specifications are subject to change.

Tesca Technologies Pvt. Ltd.

IT-2013, Ramchandrapura Industrial Area, Sitapura Extension, Near Bombay Hospital, Vidhani Circle, Jaipur-302022, Rajasthan, India, Tel: +91-141-2771791 / 2771792; Email: info@tesca.in, tesca.technologies@gmail.com Website: www.tesca.in

10/11

10/11 4

Scope of Learning:

- PC to PC Data Communication using MIC components.
- Measurement of Transmission Loss and Reflection Loss.
- Measurement of substrate dielectric constant using Ring Resonator.
- Measurement of power division, isolation and return loss characteristics.
- Measurement of coupling, isolation and return loss characteristics.
- Measurement of coupling and directivity.
- Measurement of Low Pass Filter characteristics.
- Measurement of Band Pass Filter characteristics.
- Measurement of Band Stop Filter characteristics.
- Measurement of characteristics of Patch Antennas.
- Measurement of characteristics of an MIC Amplifier.
- To study RF switch.
- To study RF Mixer.
- Measurement of Guide wavelength, Free Space Wavelength and SWR using Measuring Line.
- Measurement of Directivity and Gain of Antennas : Yagi Antenna, Patch Antenna, Dipole Antenna.
- To study the characteristics of Isolator.
- To study the characteristics of Circulator.

Accessories:

- Matched Loads (5 Nos.)
- Short
- Coaxial Detector
- Microstrip Directional Coupler (10 dB)
- SMA to SMA Adapters (Both male & female)
- SMA (male) connector fitted cables
- Attenuator (3 dB)
- +12V DC Adaptor
- Transmitting and Receiving Mast
- SMA (Male) to BNC (Female) adaptor
- 3-pin Lunar cable





: Ceramic Substrate

Ceramic Substrate

VSWR Meter:

Sensitivity	:	0.1µV for 200W input impedance for full scale deflection
Noise Level	:	Less than 0.02µV
Range	:	0 - 60 dB in 10 dB steps
Input	:	Un-biased low and high impedance crystal
		biased crystal (200 and 200K)
Meter Scale	:	SWR 1-4, SWR 3-10, dB 0-10, expand
		SWR 1-1.3, dB 0-2
Gain Control	:	Adjusts the reference level, variable range
		0-10 dB (approximate)
Input Connector	:	BNC(F)
Input Frequency	:	$1000 Hz \pm 10\%$
Power Supply	:	$230V \pm 10\%$, $50Hz/60Hz$ on request
Power consumption	:	2VA (approximate)
Dimension (mm)	:	W 262 x D 316 x H 130

Specification of MIC Components 1. Test Jig

 Test Jig It includes of the follow a) 10 dB directional could b) Detector c) Shorts d) Matched Loads e) Attenuator 	
2. Low pass Filter Cut off frequency Dielectric material Dielectric constant	2.5GHz (approximate)Ceramic Substrate3.02
3. Band Pass Filter Center frequency aroun Dielectric material Dielectric constant	d : 2.4GHz : Ceramic Substrate : 3.02
4. Band Stop Filter Center frequency aroun Dielectric material Dielectric constant	d : 2.4GHz : Ceramic Substrate : 3.02
5. Branch Line Coupler Dielectric material Dielectric constant Coupling	: Ceramic Substrate : 3.02 : 3dB
6. Rat-Race Coupler Dielectric material Dielectric constant Coupling	Ceramic Substrate3.023dB
7. Parallel Line Direction Dielectric Material Dielectric Constant Coupling	nal Coupler : Ceramic Substrate : 3.02 : 15dB
8. Power Divider Dielectric Material Output Power Return Loss Dielectric Constant	: Ceramic Substrate : 3dB : 8dB : 3.02
9. Ring Resonator The Resonance freq. Dielectric material	: 2.4GHz : Ceramic Substrate

Note: Specifications are subject to change. Tesca Technologies Pvt. Ltd.

Dielectric constant

: 3.02

IT-2013, Ramchandrapura Industrial Area, Sitapura Extension, Near Bombay Hospital, Vidhani Circle, Jaipur-302022, Rajasthan, India, Tel: +91-141-2771791 / 2771792; Email: info@tesca.in, tesca.technologies@gmail.com Website: www.tesca.in

Microwave Generator:

meroware ocherator.	
Frequency Range :	2.2 - 3GHz continuously variable.
Display :	16 x 2 LCD
Display Accuracy :	40MHz
Impedance :	50
Min RF level :	5mW
Output Level Variation :	10 - 20 dB
Operating Modes :	Sweep, CW, Int. AM, Int. FM, Ext. AM,
	PC communication
Modulating Frequency :	100Hz to 5kHz AM square wave, FM
	triangular wave
Power Supply :	230V ±10%, 50Hz
Power Consumption :	5VA (approximate)
Dimension (mm) :	W 262 x D 316 x H 130

10. 50E Microstrip Line Dielectric material

Dielectric constant : 3.02 11. RF Switch (Pin Modulator) Frequency Range : DC to 5GHz Rise/fall time : 6 ns typical SPDT Type : 12. RF Mixer Frequency Range : 2.0 to 7.0GHz Conversion Loss : 6.2dB typical L-R Isolation 30 dB typical : **RF** Power 50mW :

13. Local Oscillator

Frequency Range	: 2.2 to 3GHz
Tuning Voltage	: 5V DC
Operating Voltage	: 5V DC

14. Measuring line

Dielectric Material	
Dielectric Constant	

15. Isolator

• 15014101		
Isolation	:	15dB
Impedance	:	50 Ohms
Insertion loss	:	0.8dB Max
Avg Power	:	5W
Design Tolerance	:	±5%

:

: 3.02

16. Circulator

Isolation	:	15dB
Impedance	:	50 Ohms
Insertion loss	:	0.8dB Max
Avg Power	:	5W
Port	:	3
Design Tolerance	:	$\pm 5\%$





Features


- 3MHz-3GHz range
- 100Hz resolution
- 80dB dynamic range
- Full s-parameter test set
- De-embedding capability
- Time domain facility
- P1dBand AM-PM measurements
- Light weight and small footprint
- Low cost
- Exhaustive learning material
- 1 Year Warranty




3MHz - 3GHz Full S-Parameter Vector Network Analyser (Optional)


It is a PC-driven **Vector Network Analyser** which is suitable for measuring a wide range of devices from **3MHz to 3GHz** with 100Hz resolution. It is housed in a small lightweight package making it very portable. The user interface control software provides many useful features including memory functions, limit lines, de-embedding, time-domain and reference plane extension. Also, utilities such as measurement of power at the 1dB gain compression point and AM to PM conversion factor add versatility to the instrument.

Unique features include OSL calibration that does not require a precision load and importing of data files into memory traces for live comparison with measurements.



Transmission Characteristic of Ring Resonator (S12)






Transmission Characteristic of Ring Resonator (S11)



Software Window



Transmission Characteristic of Ring Resonator (S12)

Frequency and	ator Mode <u>[</u>]]
Freq (MHz)	Level (dBm)
[h000.0000	0 💌
Apply	Exit

Note: Specifications are subject to change.

Tesca Technologies Pvt. Ltd.

IT-2013, Ramchandrapura Industrial Area, Sitapura Extension, Near Bombay Hospital, Vidhani Circle, Jaipur-302022, Rajasthan, India, Tel: +91-141-2771791 / 2771792; Email: info@tesca.in, tesca.technologies@gmail.com Website: www.tesca.in

