



Technical Specifications

- Measuring resistor in potentiometer circuit, adjustable with rotary knob. A multi-stage decade set can be assembled in combination with other decade resistors. Includes safety connecting leads.
- Range: 0 Ω to 100 Ω Steps: 10 Ω , Max. current: 250 mA, Accuracy: 0.5%, Connection: 3 x 4-mm safety sockets,
- Dimensions: 72 mm x 72 mm x 90 mm

Note: Specifications are subject to change, Photos shown above are Indicative, Actual Product can Vary.



Export Sales: +91-9829132777
 India Sales: +91-9588842361



IT-2013, Ramchandrapura Industrial Area,
 Sitapura Extension, Jaipur-302022, India.



info@tesca.in
 www.tescaglobal.com