



Technical Specifications

- Measuring resistor in potentiometer circuit, adjustable with rotary knob. A multi-stage decade set can be assembled in combination with other decade resistors. Includes safety connecting leads.
- Range: 0 Ω to 10 Ω, Steps: 1 Ω, Max. current: 750 mA, Accuracy: 1 %, Connection: 3 x 4-mm safety sockets. Dimensions: 72 mm x 72 mm x 90 mm
- Weight: 220

Note: Specifications are subject to change, Photos shown above are Indicative, Actual Product can Vary.



Export Sales: +91-9829132777
India Sales: +91-9588842361



IT-2013, Ramchandrapura Industrial Area,
Sitapura Extension, Jaipur-302022, India.



info@tesca.in
www.tescaglobal.com