



### True-RMS Electronics Logging Multimeter

- **Counts:** 50,000
- **Voltage (AC/DC):** Up to 1000 V
- **Current (AC/DC):** Up to 10 A (with test leads and current jacks)
- **Resistance:** Up to 500 M $\Omega$
- **Capacitance:** Up to 50,000  $\mu$ F
- **Frequency:** Up to 100 kHz
- **Temperature Range:** -40 °C to 400 °C (includes thermocouple)
- **Additional Measurements:** dB, Conductance (V)
- **Features:**
  - True RMS measurement
  - Manual and auto ranging
  - Display Hold, Auto Hold
  - Min/Max/Average recording
  - Backlit digital display with analog bar graph
- **Durability:** Robust and fast with accurate readings

*Note: Specifications are subject to change, Photos shown above are Indicative, Actual Product can Vary.*



Export Sales: +91-9829132777  
India Sales: +91-9588842361



IT-2013, Ramchandrapura Industrial Area,  
Sitapura Extension, Jaipur-302022, India.



info@tesca.in  
www.tescaglobal.com