

Order Code : 20213543.9 Name : Fefroherant Gas leak Detector



Specifications:

- Power Supply: DC6V/4 \* 7# (Alkaline battery)
- Maximum sensitivity: 14g/year
- Preheating time: 6S
- Reaction time: Instantaneous
- Battery life: About 50 hours.
- Size: 170\*45\*43mm
- Package size: 23\*8.5\*5.5cm / 9.06\*3.35\*2.17in
- Package weight: 284g / 10.02oz

## Scope of use:

- Able to detect air conditioning, refrigeration system and refrigerant recovery device.
- The instrument reacts to all halogen gases. CFCs , such as R12, R11, R500, R503HCFCs, such as R22, R123, R124, R502HCFCs, such as R134a, R404a, R125
- Detect the leakage of ethylene oxide gas on medical equipment.
- Detect the SF-6 in high voltage switch.
- Detect fluorine, chlorine and bromine (halogen gas).5. Detect Halon gas in the fire extinguishing system.

## **Operation instructions:**

- After 4 \* 7# (Alkaline battery) are installed, turn on the power switch clockwise, and one red signal light will be bright, and another will be dark, indicating that the instrument is in a normal working state.
- Turn the sensitivity adjustment knob clockwise until the red signal indicator light turns bright and makes a sound like click , click. Then stop adjusting, and at this point, the detection of this instrument is at its best.

Note: Specifications are subject to change, Photos shown above are Indicative, Actual Product can Vary.

## TESCA TECHNOLOGIES PVT. LTD.

IT-2013, Ramchandrapura Industrial Area, Sitapura Extension, Jaipur-302029, Rajasthan, India. Ph/ Fax: 91-141-2771791, 2771792; Email: *info@tesca.in*, *tesca.technologies@gmail.com* Website: *www.tesca.in* 

- When detecting very dirty parts, do not touch the probe, wipe with towel or blow with compressor, do not use detergent and solvent, because the instrument reacts to their chemical composition.
- Package list:1 \* Leakage Detector1 \* User manuel\

Note: Specifications are subject to change, Photos shown above are Indicative, Actual Product can Vary.

## TESCA TECHNOLOGIES PVT. LTD.

IT-2013, Ramchandrapura Industrial Area, Sitapura Extension, Jaipur-302029, Rajasthan, India. Ph/ Fax: 91-141-2771791, 2771792; Email: **info@tesca.in**, **tesca.technologies@gmail.com** Website: **www.tesca.in**